1. INSTALL 5 /8" DIA. COPPER–CLAD OR 3 /4" DIA. GALV. STEEL X 10' LONG GROUND ROD IN FOUNDATION OF EACH POLE.
2. BOND ALL FOUR ANCHOR BOLTS.
3. TERMINATE NEUTRAL AND GROUNDING CONDUCTORS ON GROUND ROD IN BASE OF FIRST POLE RECEIVING P.G.&E. SERVICE.
4. TERMINATE GROUNDING CONDUCTORS ON GROUNDING LUG IN BASE OF ALL OTHER POLES.
5. APPLICATION: 120V OR 240V OVERHEAD SERVICE FEEDING MULTIPLE STREETLIGHTS.
6. GROUND THE MESSENGER AS REQUIRED BY NATIONAL ELECTRICAL CODE.

APPROVED BY			DRAWING NO.
AWS	OVERHEAD STREETLIGHT MULTIPLE SERVICE TYPE IIC / IID – NOTES	CITY OF SAN JOSE CALIFORNIA	E–45
DATE 3/3/92	DEPARTMENT OF PUBLIC WORKS		